## **SIEMENS**

## **Data sheet**

## 6ES7134-6HD01-0BA1



SIMATIC ET 200SP, ANALOG INPUT MODULE, AI 4XU/I 2-WIRE STANDARD, PACKING UNIT: 1 PIECE, FITS TO BU-TYPE A0, A1, COLOR CODE CC03, MODULE DIAGNOSIS, 16BIT,  $\pm$ 1-0,3%

General information	
Product type designation	AI 4x U/I 2-wire
HW functional status	From FS02
Firmware version	
<ul> <li>FW update possible</li> </ul>	Yes
usable BaseUnits	BU type A0, A1
Color code for module-specific color identification plate	CC03
Product function	
● I&M data	Yes; I&M0 to I&M3
<ul> <li>Isochronous mode</li> </ul>	No
Measuring range scalable	No
Engineering with	
<ul> <li>STEP 7 TIA Portal configurable/integrated from version</li> </ul>	V14 / -
<ul> <li>STEP 7 configurable/integrated from version</li> </ul>	V5.6 and higher
<ul> <li>PCS 7 configurable/integrated from version</li> </ul>	V8.1 SP1
<ul> <li>PROFIBUS from GSD version/GSD revision</li> </ul>	One GSD file each, Revision 3 and 5 and higher
<ul> <li>PROFINET from GSD version/GSD revision</li> </ul>	GSDML V2.3
Operating mode	
<ul> <li>Oversampling</li> </ul>	No
• MSI	No
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	No
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	37 mA; without sensor supply
Encoder supply	
24 V encoder supply	
• 24 V	Yes
Short-circuit protection	Yes
<ul> <li>Output current, max.</li> </ul>	20 mA; max. 50 mA per channel for a duration < 10 s
Power loss	
Power loss, typ.	0.85 W; Without encoder supply voltage
Address area	
Address space per module	
<ul> <li>Address space per module, max.</li> </ul>	8 byte; + 1 byte for QI information

Hardware configuration	
	Yes
Automatic encoding	Yes
Mechanical coding element  Type of machanical coding element	
Type of mechanical coding element  Selection of BaseUnit for connection variants	Type A
	DILlama AO A4
2-wire connection	BU type A0, A1
Analog inputs	
Number of analog inputs	4; Differential inputs
permissible input voltage for voltage input (destruction limit), max.	30 V
permissible input current for current input (destruction limit), max.	50 mA
Cycle time (all channels), min.	Sum of the basic conversion times and additional processing times (depending on the parameterization of the active channels)
Input ranges (rated values), voltages	
• 0 to +10 V	Yes; 15 bit
<ul><li>— Input resistance (0 to 10 V)</li></ul>	120 kΩ
• 1 V to 5 V	Yes; 15 bit
<ul><li>— Input resistance (1 V to 5 V)</li></ul>	120 kΩ
• -10 V to +10 V	Yes; 16 bit incl. sign
— Input resistance (-10 V to +10 V)	120 kΩ
• -5 V to +5 V	Yes; 16 bit incl. sign
— Input resistance (-5 V to +5 V)	120 kΩ
Input ranges (rated values), currents	
• 0 to 20 mA	Yes; 15 bit
— Input resistance (0 to 20 mA)	100 Ω; + approx. 0.7 V diode forward voltage
• 4 mA to 20 mA	Yes; 15 bit
— Input resistance (4 mA to 20 mA)	100 Ω; + approx. 0.7 V diode forward voltage
Cable length	upp.o v d.odo io. nata tonago
• shielded, max.	1 000 m; 200 m for voltage measurement
Analog value generation for the inputs	
Measurement principle	integrating (Sigma-Delta)
Integration and conversion time/resolution per channel	3. 4 3 (0.3 20)
Resolution with overrange (bit including sign), max.	16 bit
<ul> <li>Integration time, parameterizable</li> </ul>	Yes
Integration time, parameterizable     Interference voltage suppression for interference	16.6 / 50 / 60 Hz
- interference voltage supplession for interference	
frequency f1 in Hz	
	180 / 60 / 50 ms
frequency f1 in Hz	
frequency f1 in Hz  • Conversion time (per channel)  Smoothing of measured values	180 / 60 / 50 ms
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels	
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels  parameterizable	180 / 60 / 50 ms 4; None; 4/8/16 times
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels  parameterizable  Encoder	180 / 60 / 50 ms 4; None; 4/8/16 times
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels  parameterizable  Encoder  Connection of signal encoders	180 / 60 / 50 ms  4; None; 4/8/16 times Yes
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement	180 / 60 / 50 ms  4; None; 4/8/16 times Yes
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes  Yes
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels  parameterizable  Encoder  Connection of signal encoders  for voltage measurement  for current measurement as 2-wire transducer  Burden of 2-wire transmitter, max.	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes Yes 650 Ω
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels  parameterizable  Encoder  Connection of signal encoders  for voltage measurement  for current measurement as 2-wire transducer  Burden of 2-wire transmitter, max.  for current measurement as 4-wire transducer	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes  Yes
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels parameterizable  Encoder  Connection of signal encoders  for voltage measurement for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No  0.01 %
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No  0.01 % 0.005 %/K
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes  Yes  650 Ω  No  0.01 %  0.005 %/K  50 dB
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No  0.01 % 0.005 %/K
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)  Operational error limit in overall temperature range	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes  Yes  650 Ω  No  0.01 %  0.005 %/K  50 dB
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes  Yes  650 Ω  No  0.01 %  0.005 %/K  50 dB
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)  Operational error limit in overall temperature range	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)  Operational error limit in overall temperature range Voltage, relative to input range, (+/-)	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %  0.5 %
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels parameterizable  Encoder  Connection of signal encoders  for voltage measurement for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)  Operational error limit in overall temperature range  Voltage, relative to input range, (+/-)  Current, relative to input range, (+/-)	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %  0.5 %
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels parameterizable  Encoder  Connection of signal encoders  for voltage measurement for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)  Operational error limit in overall temperature range  Voltage, relative to input range, (+/-)  Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %  0.5 %  0.5 %
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)  Operational error limit in overall temperature range  Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) Voltage, relative to input range, (+/-)	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %  0.5 %  0.5 %  0.3 % 0.3 % 0.3 %
frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels parameterizable  Encoder  Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)  Operational error limit in overall temperature range  Voltage, relative to input range, (+/-) Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C) Voltage, relative to input range, (+/-) Current, relative to input range, (+/-)	180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %  0.5 %  0.5 %  0.3 % 0.3 % 0.3 %

Common mode voltage, max.	10 V
Common mode interference, min.	90 dB
Interrupts/diagnostics/status information	
Diagnostics function	Yes
Alarms	
Diagnostic alarm	Yes
Limit value alarm	No
Diagnoses	
Monitoring the supply voltage	Yes
Wire-break	Yes; at 4 to 20 mA
• Short-circuit	Yes; with 1 to 5 V or 2-wire mode: Short-circuit of the encoder supply to ground or of an input to the encoder supply
Group error	Yes
Overflow/underflow	Yes
Diagnostics indication LED	
Monitoring of the supply voltage (PWR-LED)	Yes; green LED
Channel status display	Yes; green LED
• for channel diagnostics	No
for module diagnostics	Yes; green/red LED
Potential separation	
Potential separation channels	
• between the channels	Yes; channel group-specific between 2-wire current input group and voltage input group
<ul> <li>between the channels and backplane bus</li> </ul>	Yes
<ul> <li>between the channels and the power supply of the electronics</li> </ul>	Yes; only for voltage inputs
Permissible potential difference	
between the inputs (UCM)	10 V DC
Isolation	
Isolation tested with	707 V DC (type test)
Standards, approvals, certificates	
Suitable for applications according to AMS 2750	Yes; Declaration of Conformity, see online support entry 109757262
Suitable for applications according to CQI-9	Yes
Ambient conditions	
Ambient temperature during operation	
horizontal installation, min.	-30 °C; < 0 °C as of FS02
<ul> <li>horizontal installation, max.</li> </ul>	60 °C
• vertical installation, min.	-30 °C; < 0 °C as of FS02
• vertical installation, max.	50 °C
Altitude during operation relating to sea level	
Installation altitude above sea level, max.	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	15 mm
	73 mm
Height	
Depth	58 mm
	58 mm

6ES71346HD010BA1 Page 3/3

last modified:

9/7/2023